TECHNOLOGY SYSTEMS GENERAL NOTES **ELECTRONIC SECURITY SYSTEM** BASIC MATERIALS BROADBAND TELEVISION SYSTEM CONDUIT TURNED UP CR CARD READER, WALL MOUNTED REFER TO SPECIFICATION SECTION "TECHNOLOGY GENERAL PROVISIONS" FOR MORE INFORMATION ABOUT DRAWINGS AND BID DOCUMENTS RX ANTENNA CONDUIT TURNED DOWN CK CARD READER WITH INTEGRATED KEYPAD, WALL MOUNTED NAMY SYMBOLS USED IN THIS PROJECT HAVE A TYPE ASSOCIATED WITH THEM. SEE SHEETS WITH DETAILS AND PROJECT SPECIFICATIONS FOR MORE TX ANTENNA CAPPED CONDUIT BR BIOMETRIC ACCESS CONTROL DEVICE, WALL MOUNTED INFORMATION ON THE DESCRIPTION OF EACH TYPE. ——] CONDUIT STUBBED AND BUSHED INTO ACCESSIBLE CEILING CAVITY KP KEYPAD, WALL MOUNTED 3. ALL CONDUIT FOR TECHNOLOGY SYSTEMS INDOOR ABOVE GRADE SHALL BE EMT AND ALL CONDUIT FOR BELOW GRADE SHALL BE PV ζ TX/RX ANTENNA — CONDUIT CONTINUED IP WIRED IP LOCK, DOOR MOUNTED -() 2 WAY SPLITTER SEE LIFE SAFETY PLANS FOR LOCATIONS OF FIRE RATED PARTITIONS IN THIS PROJECT. PROVIDE AN APPROVED FIRE STOP SYSTEMS FOR EACH WM WIRELESS MORTISE LOCK, DOOR MOUNTED RACEWAY OR CABLE GOING THROUGH A RATED WALL. SEE SPECIFICATION "RACEWAYS FOR TECHNOLOGY" FOR MORE INFORMATION. -() 3 WAY SPLITTER X= QTY OF SLEEVES WC WIRELESS CYLINDRICAL LOCK, DOOR MOUNTED 5. WORKING CLEARANCES AROUND ELECTRICAL EQUIPMENT SHALL BE MAINTAINED IN COMPLIANCE WITH THE NATIONAL ELECTRICAL CODE ARTICLE 110 Y= SIZE OF CONDUITS SLEEVES PENETRATING WALL ABOVE CEILING SPACE. -() = 4 WAY SPLITTER IK INTRUSION ALARM KEYPAD COORDINATE EQUIPMENT INSTALLATION TO MAINTAIN REQUIRED CLEARANCES. - (■ 8 WAY SPLITTER IF NO QUANTITY INDICATED USE AS MANY SLEEVES AS REQUIRED TO MATCH CROSS ELECTRIC MORTISE LOCK OR ELECTRIC TRIM SECTIONAL AREA OF CABLE TRAY NEXT TO SLEEVE. S. SYMBOLS USED ON THE TECHNOLOGY DRAWINGS ARE NOT THE SAME SIZE AS THE ACTUAL OBJECT BEING REPRESENTED. THEREFORE LOCATIONS OF (SD) SATELLITE DISH THE SYMBOLS ON THE FLOOR PLANS ARE AN APPROXIMATION TO THE ACTUAL LOCATION OF THE DEVICE AND NEED TO BE CAREFULLY COORDINATED DELAYED EGRESS LATCH LOCK **CATV AMPLIFIER** TUBULAR RUNWAY, HUNG ABOVE CEILING OR AS NOTED WITH OTHER ELEMENTS IN THE VICINITY. AS A GENERAL GUIDELINE: I= INPUT LEG DELAYED EGRESS MAG LOCK A. VOICE/DATA OUTLET FOR WORK-AREAS SHALL BE INSTALLED WITHIN 6 INCHES OF A POWER OUTLET INDICATED IN ELECTRICAL DRAWINGS. CABLE TRAY (TYPE), HUNG ABOVE CEILING OR AS NOTED O O= OUTPUT LEG B. TV OUTLETS SHALL BE INSTALLED WITHIN 6 INCHES OF A POWER OUTLET SHOWN ON THE ELECTRICAL DRAWINGS. ELECTRIC CYLINDRICAL LOCK T= TEST PORT). WHEN MULTIPLE TECHNOLOGY SYSTEMS OUTLETS ARE INDICATED NEXT TO EACH OTHER WITH SYMBOLS, THE SPACING BETWEEN OUTLETS SHALL BE SURFACE MOUNTED ENCLOSED TECHNOLOGY SYSTEMS. SEE SHEETS WITH DETAILS FOR X= AMPLIFIER TYPE - SP: SERVICE PROVIDER, H: HEADEND AMPLIFIER, D: DISTRBUTION AMPLIFIER CONSISTENT IF NO ELEVATION IS SHOWN ON THE DRAWINGS. ADDITIONAL INFORMATION ELECTRIC LATCH RETRACTION LOCK D. WHEN INSTALLER IS NOT CERTAIN ABOUT SPECIFIC ADJACENCIES OF A DEVICE, THE QUESTION SHALL BE ASKED TO THE ENGINEER PRIOR TO DISTRIBUTION TAP JUNCTION BOX WALL MOUNTED. SIZE PER NEC IF NOT INDICATED ON DRAWING. NEMA 1 FOR (M) ELECTROMAGNETIC LOCK INSTALLATION. INTERIOR, NEMA 4X FOR EXTERIOR USE WITH HINGED COVER AND LOCKING COVER a I= INPUT LEG O= OUTPUT LEG (D) ELECTRONIC DETENTION LOCK JUNCTION BOX CEILING MOUNTED. SIZE PER NEC IF NOT INDICATED ON DRAWING. NEMA 1 FOR '. FOR EXACT LOCATION OF CEILING MOUNTED EQUIPMENT REFER TO THE ARCHITECTURAL REFLECTED CEILING PLAN. LOCATIONS OF EQUIPMENT NOT T= TAP LEGS, QTY AS INDICATED IN RISER INTERIOR, NEMA 4X FOR EXTERIOR USE WITH HINGED COVER AND LOCKING COVER INCLUDED ON THE REFLECTED CEILING PLAN SHALL BE COORDINATED WITH THOSE ITEMS SHOWN. COORDINATION OF CEILING MOUNTED EQUIPMENT **ES** ELECTRIC DOOR STRIKE DIRECTIONAL COUPLER SHALL BE PRIOR TO ANY ROUGH-IN. NOTIFY ENGINEER OF ANY DISCREPANCY. TELECOMMUNICATIONS GROUND VAULT. SEE DETAILS AND SPECS FOR MORE INFORMATION X= BOX TYPE. IF NOT SHOWN, ONLY ONE TYPE IN PROJECT © ELECTRIC DOOR OPERATOR (ACTUATOR ARM) \ _ l= INPUT LEG O= OUTPUT LEG B. LOCATIONS OF FLOOR BOXES AND FLOOR PENETRATIONS SHALL NOT BE MEASURED FROM THIS SET OF DRAWINGS, INSTALLER SHALL REQUEST PRECISE **DPS** DOOR POSITION SWITCH TELECOMMUNICATIONS PULLBOX. SEE DETAILS AND SPECS FOR MORE INFORMATION T= TAP LEGS, QTY AS INDICATED IN RISER TELECOMMUNICATIONS TOLLBOX. SEE EXECUTION OF TYPE IN PROJECT X = BOX TYPE. IF NOT SHOWN, ONLY ONE TYPE IN PROJECT BMS BALANCED MAGNETIC SWITCH CATV TAP DEFINITION TAG 9. EACH VOICE/DATA RJ45 JACK SHALL BE CONNECTED TO A DEDICATED 4 PR CABLE TECHNOLOGY POLE. SEE SHEETS WITH DETAILS FOR ADDITIONAL INFORMATION X= NUMBER OF TAP LEGS PIM MODULE FOR WIRELESS LOCKS. WALL MOUNTED Y= TAP VALUE IN dB +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF). THE RESPONSIBILITY OF RACEWAY INSTALLATION SHALL BE AS DIRECTED BY THE CONSTRUCTION MANAGER OR GENERAL CONTRACTOR, BUT ALL **GENERAL CATV EQUALIZER** RACEWAYS FOR TECHNOLOGY ARE TO BE INCLUDED IN THIS CONTRACT. ALARM, BLUE LIGHT, WALL MOUNTED +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF X= EQUALIZING VALUE IN dB I= INPUT LEG 1. WHEN CONDUIT RUNS ARE INDICATED ABOVE GRADE OR BELOW GRADE ON THESE DRAWINGS, NOT EVERY SINGLE JUNCTION BOX (OR NEW EQUIPMENT LOCAL ALARM - HORN/STROBE, WALL MOUNTED +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF COMMUNICATIONS VAULT) REQUIRED IS INDICATED ON THE DRAWINGS. TYPICALLY ONLY END POINT LOCATIONS OR SPECIFIC PASS-THROUGH LOCATIONS O= OUTPUT LEG EXISTING WORK AND/OR EQUIPMENT REFERENCE, SHOWN ON MULTIPLE DRAWINGS WHERE THE ENGINEER DESIRES A BOX ARE SHOWN ON THE DRAWINGS. SEE SPECIFICATION "RACEWAYS FOR TECHNOLOGY" FOR REQUIREMENTS THAT TERMINATOR SIREN ALARM FOR INTRUSION DETECTION, WALL MOUNTED INDICATE ADDITIONAL JUNCTION BOXES OR COMMUNICATION VAULTS THAT SHALL BE PROVIDED UNDER THIS CONTRACT. SUCH REQUIREMENTS INCLUDE +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF - DEVICE TO BE REMOVED (DEMO PLANS) UNDERFLOOR CONDUIT (NEW PLANS) - SURGE SUPRESSOR AT BUILDING ENTRY POINT ADDITIONAL BOXES REQUIRED BECAUSE OF NUMBER OF CONDUIT BENDS OR CHANGES IN ELEVATION. ── WIRE AND/OR CONDUIT RUN CONTINUED ON REFERENCED DETAIL ASSISTANCE STATION, WALL MOUNTED TELEVISION OUTLET, COORDINATE ROUGH-IN WITH TV MOUNT INSTALLER, CEILING MOUNTED SOME SYMBOLS INCLUDED IN THE SYMBOL LEGEND MAY NOT BE USED IN THESE PROJECT DRAWINGS. X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT, REFER TO SPECIFICATION FOR TYPE X= DENOTES TYPE OF OUTLET, SEE DETAIL FOR MORE INFORMATION **----** MATCH LINE REFERENCING CONTINUATION ON OTHER DRAWINGS +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF ${\sf U}={\sf USER}$ (IF APPLICABLE). THIS ONLY APPLIES TO DATA AND FIBER NOT COAX 3. UNDER NO CONDITIONS, CONDUITS FOR LOW VOLTAGE FOR FLOOR BOXES SHALL BE DAISY CHAINED TOGETHER BETWEEN ADJACENT FLOOR BOXES. - - DETAIL AND/OR SECTION REFERENCE +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF ASSISTANCE STATION (BLUE LIGHT), TOWER STATION ALL CONDUITS FOR FLOOR BOXES SHALL BE HOME RUNS TO NEAREST ACCESSIBLE CEILING SPACE. X X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT, REFER TO SPECIFICATION FOR TYPE TELEVISION OUTLET, COORDINATE ROUGH-IN WITH TV MOUNT INSTALLER, WALL MOUNTED CABLE ROUTING BOUNDARY X= DENOTES TYPE OF OUTLET, SEE DETAIL FOR MORE INFORMATION 4. THIS SET OF DRAWINGS DOES NOT INDICATE ALL GROUNDING AND BONDING REQUIREMENTS FOR TECHNOLOGY SYSTEMS. REFER TO SPECIFICATION INTERCOM SUBSTATION (DOOR STATION), WALL MOUNTED — FUTURE WORK SECTION "GROUNDING FOR TELECOMMUNICATION SYSTEM" FOR ADDITIONAL REQUIREMENTS. U=USER(IF APPLICABLE). THIS ONLY APPLIES TO DATA AND FIBER NOT COAX X = TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT, REFER TO RISER FOR TYPE +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF DRAWING NOTES AND DESIGNATIONS 5. ALL CABLES FOR TECHNOLOGY SYSTEMS RUN UNDER SLAB OR BELOW GRADE IN CONDUITS STUBBING UP INSIDE THE TELECOM ROOM SHALL BE INTERCOM MASTER STATION, DESK MOUNTED AUDIO VISUAL EQUIPMENT INDOOR/OUTDOOR RATED. FOR CONDUITS STUBBING UP IN OTHER LOCATIONS DIFFERENT FROM TELECOM ROOMS AND FURTHER THAN 50 FT. FROM A X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT, REFER TO RISER FOR TYPE TELECOM ROOM, DO NOT USE INDOOR/OUTDOOR RATED CABLES. (x) DRAWING KEYED NOTES INTERCOM MASTER STATION, WAII MOUNTED **CEILING MOUNTED SPEAKER** 16. GRAPHICS USED FOR EQUIPMENT IN ELEVATIONS AND CHANNELS (LINE DRAWINGS) DO NOT NECESSARILY REPRESENT THE PART NUMBER OF THE X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT, REFER TO RISER FOR TYPE X= SPEAKER TYPE EQUIPMENT SPECIFIED. THE PART NUMBERS LISTED IN THE DRAWINGS AND SPECIFICATIONS ARE TO BE FOLLOWED FOR BASIS OF DESIGN, NOT THE +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF DETAIL OR SECTION REFERENCE TAG Y= SPEAKER ZOINL
Y-Z Z= DENOTES SPEAKER # IN ZONE GRAPHICS. CALL STATION (THROUGH PHONE LINE) FOR BUILDING ENTRY, WALL MOUNTED $_{ ext{+} ext{H}}$ +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF W W= DENOTES SPEAKER WATTAGE TAP 7. THE TECHNOLOGY DRAWINGS DO NOT SHOW ALL REQUIRED CONDUITS/RACEWAYS TO BE PROVIDED UNDER THIS CONTRACT. TYPICALLY CONDUIT **VOICE AND DATA SYSTEM** NO ZONE INDICATES LOCAL ZONE FOR A/V SYSTEM IN ROOM DOOR TYPE IDENTIFIER SLEEVES SMALLER THAN 2" ARE NOT SHOWN ON THE DRAWINGS. SEE SPECIFICATIONS "RACEWAYS FOR TECHNOLOGY" AND DRAWING DETAILS FOR X= TYPE (A1,C3,B6..) REFER TO SECURITY DOOR DETAILS ADDITIONAL RACEWAY REQUIREMENTS. WALL MOUNTED SPEAKER DOOR RELEASE BUTTON, WALL MOUNTED TELECOMMUNICATION OUTLET X= SPEAKER TYPE X= A: ADA ACCESSIBLE - (PALM ACTUATOR), W: HAND WAVE, NO TYPE: REGULAR PUSH BUTTON 18. DEFINITION OF ACRONYMS USED IN THESE DRAWINGS: X= MOUNTING: (E= EXISTING, F= FLUSH, S= SURFACE, M= MODULAR FURNITURE ADAPTER, Y= SPEAKER ZOIL
Y-Z Z= DENOTES SPEAKER # IN ZONE Y= SPEAKER ZONE A. NIC (N.I.C.) - NOT IN CONTRACT P= POLE, L= FLOOR, R= RACEWAY) O DOOR RELEASE BUTTON, DESK MOUNTED B. OFE (O.F.E.) = OWNER FURNISHED EQUIPMENT. SEE RESPONSIBILITY MATRIX FOR MORE INFORMATION. N= NUMBER OF DATA CABLES IN THE FACEPLATE W. W= DENOTES SPEAKER WATTAGE TAP C. DHI (D.H.I.) = DOOR HARDWARE INSTALLER REX REQUEST TO EXIT DEVICE (IR SENSOR), MOUNT CENTERED ABOVE DOOR FRAME Y= NOT USED +H= MOUNTING HEIGHT IN INCHES AT CENTER OF DEVICE D. USC (U.S.C.) = UNDER SEPARATE CONTRACT Z= NUMBER OF FIBER OPTIC STRANDS IN THE FACEPLATE NO ZONE INDICATES LOCAL ZONE FOR A/V SYSTEM IN ROOM GLASS BREAK SENSOR, WALL MOUNTED +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 7'-0" AFF U= USER(IF APPLICABLE) 19. ALL REQUIRED WALL PENETRATIONS, EXISTING AND NEW, SHALL MAINTAIN THE NEW WALL RATING AFTER CABLING HAS BEEN INSTALLED OR REMOVED. VOLUME CONTROL, WALL MOUNTED +H= INSTALLATION HEIGHT IN INCHES AT CENTER OF OUTLET, COORDINATE WITH +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF ELECTRICAL. IF NOT SHOWN INSTALL AT TYPICAL RECEPTACLE HEIGHT. (GB) GLASS BREAK SENSOR, CEILING MOUNTED 20. ALL SPEAKERS MOUNTED IN A CEILING TILE SHALL BE CENTERED IN THE CEILING TILE. W= WALL TELEPHONE FACEPLATE WITH SUPPORT STUDS, INSTALLED AT 48" AFF AT CENTER FT FLIP TOP DEVICE MOUNTED ON TABLE GP GATE PEDESTAL OF OUTLET AND 12" FROM EDGE OF WALL. SENS MICROPHONE FOR AMBIENT NOISE, WALL MOUNTED WP=WEATHERPROOF SENS MICKUPHONE FOR AWIDIENT NOISE, WALL WOODS TEE +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 8'-0" AFF GO ELECTRIC GATE OPERATOR SECURITY SYSTEM GENERAL NOTES DURESS PANIC BUTTON, WALL MOUNTED +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF EXAMPLE: F2 = TWO DATA JACKS IN A SINGLE FACEPLATE, FLUSH MOUNTED SM SENS MICROPHONE FOR AMBIENT NOISE, CEILING MOUNTED MECH OUTLET FOR MECHANICAL/ ELECTRICAL/ FIRE ALARM/ ELEVATOR/ STAR CONNECTION MICROPHONE, DESK MOUNTED SYMBOLS USED TO REPRESENT DEVICES SUCH AS CCTV CAMERAS, INTERCOM STATIONS, SECURITY WORKSTATIONS, CALL STATIONS, AND EMERGENCY D DURESS PANIC BUTTON, MOUNTED UNDER DESK Y: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT PHONE STATIONS REQUIRE ONE (1) DATA DROP FOR SUCH DEVICE. THIS DATA DROP IS NOT SHOWN ON THE VOICE/DATA FLOOR PLANS, BUT SHALL BE U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET -MD MOTION DETECTOR, WALL MOUNTED, MOUNT 6" BELOW CEILING OR 8'-0" AFF MAX PROVIDED FOLLOWING ALL REQUIREMENTS FOR VOICE/DATA DROPS INDICATED IN THE DRAWING DETAILS AND IN THE SPECIFICATION "STRUCTURED MICROPHONE, WALL MOUNTED +H= IF NOT SHOWN, COORDINATE EXACT LOCATION WITH DEVICE CABLING SYSTEM". H X= DENOTES TYPE OF OUTLET, IF NOT SHOWN, ONLY ONE TYPE MD MOTION DETECTOR, 360 DEGREE SENSOR, CEILING MOUNTED CEILING MOUNTED INFORMATION OUTLET, MOUNTED ON FINISHED CEILING +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET XY: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET INFANT ABDUCTION SYSTEM, WALL MOUNTED 2. ANY DATA DROPS FOR SECURITY DEVICES EXCEEDING 295 FT. OF PERMANENT LINK DISTANCE TO THE TELECOM ROOM WHERE CAMERA WILL BE WIRED +H = MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 8'-0" AFF MICROPHONE, CEILING MOUNTED U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET TO, SHALL BE WIRED WITH FIBER OPTICS FOR HORIZONTAL CABLING AND A 2 CONDUCTOR AWG-16 CL2(P) CABLE. THE FIBER CABLE SHALL BE AS $^{\text{WO}}_{\text{X}}$ X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT DESCRIBED IN SPECIFICATION "STRUCTURED CABLING SYSTEM". IF NO INDICATION IN SUCH SPECIFICATION, FIBER OPTIC CABLE SHALL BE A 2-STRAND OM1 WAP OUTLET FOR WIRELESS ACCESS POINT, WALL MOUNTED (A) INFANT ABDUCTION SYSTEM, CEILING MOUNTED ABOVE DOOR Y: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET WIRELESS ANTENNA FOR WIRELESS MICRPHONE, WALL MOUNTED CABLE WITH A SUITABLE JACKET FOR THE APPLICATION. +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 8'-0" AFF U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET LINE BETWEEN SECURITY DEVICES, INDICATES ASSOCIATED EQUIPMENT ALL DOUBLE DOORS THAT ARE SHOWN WITH TWO DOOR POSITIONS SWITCHES ARE TO RECEIVE (1) DOOR POSITION SWITCH ON EACH DOOR LEAF AND +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 8'-0" AFF TOUCH SCREEN FOR AUDIO/VIDEO CONTROL, DESK MOUNTED WAP OUTLET FOR WIRELESS ACCESS POINT, MOUNTED ON FINISHED CEILING X= DENOTES TYPE OF OUTLET, SEE RISER FOR MORE INFO, IF NOT SHOWN, ONLY ONE TYPE SHALL REPORT AS ONE ALARM POINT. $\epsilon + \infty$ CONTROLLED DOOR INTERLOCK GROUP. PROGRAMMED SO ONLY ONE DOOR CAN BE OPEN AT A XY: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET TIME. TOUCH SCREEN FOR AUDIO/VIDEO CONTROL, WALL MOUNTED, INCLUDES BACK BOX I. ALL CAMERAS, CARD READERS AND/OR KEYPADS DEDICATED FOR ELEVATOR FLOOR SELECTION CONTROL ARE SHOWN INSIDE THE ELEVATOR CAB ON THE U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET X= DENOTES TYPE OF OUTLET. SEE RISER FOR MORE INFO. IF NOT SHOWN, ONLY ONE TYPE ACCESS CONTROL DOOR DIRECTION, A1/A2 - REPRESENTS ACCESS CONTROL PATH LOWEST LEVEL FLOOR PLAN TO WHICH THE ELEVATOR TRAVELS. +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF FREE - NO ACCESS CONTROL FLOOR BOX FOR TECHNOLOGY SYSTEMS AND POWER OUTLETS. REFER TO POKE-THRU/ CAMERA FOR AV SYSTEM, WALL MOUNTED A11 CR - CARD READER 5. LOCATION OF SURVEILLANCE CAMERAS SHALL BE CLOSELY COORDINATED WITH OTHER TRADES TO AVOID OBSTRUCTIONS IN THE FIELD OF VIEW. IT IS FLOORBOX SCHEDULE FOR MORE INFORMATION N BIOMETRIC - BIOMETRIC READER NOT REQUIRED FOR CAMERAS TO BE MOUNTED IN CENTER OF A CEILING TILE (OR CENTER OF A HALLWAY) IF THAT LOCATION CAUSES AN OBSTRUCTION IN CR/KP - CARD READER AND KEYPAD X= DENOTES TYPE OF OUTLET, SEE RISER FOR MORE INFO, IF NOT SHOWN, ONLY ONE TYPE F= FLOOR CONDITION: (C= CONCRETE TYPE, G= GRADE, R= RAISED FLOOR, W= WOOD) THE FIELD OF VIEW OF THE CAMERA. ALL CAMERAS ARE TO BE INSTALLED AS TO MINIMIZE THE OBSTRUCTIONS IN THE FIELD OF VIEW WITHIN A 4' RADIUS +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET Y= DENOTES # OF GANGS (1,2,3...) OF THE SPECIFIED LOCATION. MONITORED - DOOR MONITORED CAMERA FOR AV SYSTEM, CEILING MOUNTED Z= DENOTES PLATE TYPE (A,B,C....), A= NO AUDIO/VISUAL X= DENOTES TYPE OF OUTLET, SEE RISER FOR MORE INFO, IF NOT SHOWN, ONLY ONE TYPE LN= AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET S. SURVEILLANCE CAMERAS INDICATED IN THE CORNER OF A ROOM SHALL BE INSTALLED AS CLOSE AS PHYSICALLY POSSIBLE TO THE CORNER OF THE ROOM VIDEO SURVEILLANCE SYSTEMS U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET TO GAIN THE BEST FIELD OF VIEW FOR THAT CAMERA. ASSISTED LISTENING TRANSMITTER, WALL MOUNTED PAN/TILT/ZOOM CCTV CAMERA, WALL MOUNTED '. EACH ACCESS CONTROLLED DOOR IN THE PROJECT HAS A DOOR IDENTIFIER SYMBOL THAT ASSOCIATES THE DOOR TO A CORRESPONDING ROUGH-IN POKE-THRU FOR TECHNOLOGY SYSTEMS AND POWER OUTLETS. REFER TO POKE-THRU & ROOM SCHEDULING PANEL, WALL MOUNTED, INCLUDES BACK BOX $\bigcup_{X,C} X = CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER$ DETAIL IN THE DRAWINGS AND A SPECIFIC FUNCTIONALITY OF THE DOOR IN THE SECURITY SPECIFICATIONS. FLOOR BOX SCHEDULE FOR MORE INFORMATION X= DENOTES TYPE OF OUTLET, SEE RISER FOR MORE INFO, IF NOT SHOWN, ONLY ONE TYPE PAN/TILT/ZOOM CCTV CAMERA, CEILING MOUNTED

X,C X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 4'-0" AFF **TECHNOLOGY DRAWING INDEX** Y= DENOTES POKE-THRU SIZE (4=4", 6=6" 8=8".....) Z= DENOTES PLATE TYPE (A,B,C....), A= NO AUDIO/VISUAL OCCUPANCY SENSOR, CEILING MOUNTED FIXED CCTV CAMERA, WALL MOUNTED LN= AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET X= TYPE, C= CRESNET, E= ETHERNET SHEET DESCRIPTION $\bigcup_{X,C} X = CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER$ U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET TECHNOLOGY SYMBOLS, LEGEND, NOTES AND INDEX AUDIO VISUAL DISPLAY FIXED CCTV CAMERA, CEILING MOUNTED TT= DISPLAY TYPE WITH MOUNT WALL MOUNTED FURNITURE FEED USED TO FEED CABLES TO MODULAR FURNITURE OR CABLES X.C X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER ECHNOLOGY RESPONSIBILITY MATRIX ^^ XX= SCREEN SIZE FLOOR BOX USED TO FEED CABLES TO MODULAR FURNITURE, REFER TO DETAIL SHEET X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT SITE PLAN - TECHNOLOGY T101 180° CCTV CAMERA, WALL MOUNTED YY= HEIGHT TO CENTER OF SCREEN T102 ENLARGED SITE PLANS - TECHNOLOGY $\bigvee_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER POKE-THRU USED TO FEED CABLES TO MODULAR FURNITURE, REFER TO DETAIL SHEET INTERACTIVE WHITEBOARD FLOOR PLAN - TECHNOLOGY 180° CCTV CAMERA, CEILING MOUNTED TT= DISPLAY TYPE WITH MOUNT Σ_{X} X= TYPE, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT TECHNOLOGY RISER DIAGRAMS $\bigvee_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER **≠** xx ^^ XX= SCREEN SIZE TECHNOLOGY DETAILS AV BACKBOX, INSTALLED BEHIND DISPLAY/ CREDENZA RACK, COORDINATE BACKBOX PRIOR TO 180° MULTI-IMAGER CCTV CAMERA, WALL MOUNTED YY= HEIGHT TO CENTER OF SCREEN XT003 T EQUIPMENT SCHEDULE ROUGH-IN. REFER TO DETAIL & SCHEDULE FOR MORE INFORMATION $\mathbb{Z}_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER OVERHEAD PROJECTOR WITH MOUNT U G= DENOTES # OF GANGS 180° MULTI-IMAGER CCTV CAMERA, CEILING MOUNTED X X X= TYPE +H XY= AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET $\mathbb{Z}_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET Y= LENS THROW RATIO 360° CCTV CAMERA, WALL MOUNTED +H= MOUNTING HEIGHT IN INCHES AT CENTER OF DEVICE PULLDOWN PROJECTION SCREEN X= DIAGONAL DIMENSION IN INCHES $\mathcal{Y}_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER RECESS IN-WALL STORAGE BOX, INSTALLED BEHIND DISPLAY, COORDINATE BACKBOX PRIOR TO 360° CCTV CAMERA, CEILING MOUNTED MOTORIZED PROJECTION SCREEN X= DIAGONAL DIMENSION IN INCHES U G= DENOTES # OF GANGS $\bigvee_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER +H XY= AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET 360° MULTI-IMAGER CCTV CAMERA, WALL MOUNTED S_{LV} WALL SWITCH FOR MOTORIZED SCREEN U: AS DESCRIBED FOR TELECOMMUNICATIONS OUTLET $\bigotimes_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER +H= MOUNTING HEIGHT IN INCHES AT CENTER OF DEVICE PODIUM FOR AV EQUIPMENT, REFER TO DETAIL SHEETS 360° MULTI-IMAGER CCTV CAMERA, CEILING MOUNTED $_{X,C}$ X= CAMERA TYPE (1,2,3), SEE DETAIL SHEETS FOR MORE INFORMATION, C = CAMERA NUMBER X= DENOTES TYPE OF OUTLET, IF NOT SHOWN, ONLY ONE TYPE IN PROJECT AV PLATE OUTLET, REFER TO DETAIL SHEETS CCTVFLAT PANEL DISPLAY WITH MOUNT X= DENOTES TYPE OF OUTLET, SEE DETAIL FOR MORE INFO, IF NOT SHOWN, ONLY ONE TYPE ₹XX XX= SCREEN SIZE +H +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 1'-6" AFF +YY YY= HEIGHT TO CENTER OF SCREEN SOUND BAR WITH CAMERA, WALL MOUNTED SECURITY SYSTEM WORKSTATION, DESK MOUNTED $_{ extsf{+}}$ +H= MOUNTING HEIGHT IN INCHES AT CENTER OF OUTLET, IF NOT SHOWN, INSTALL AT 8'-0" AFF X= TYPE

> TLC ENGINEERING ©Copyright 2019 13099 S. Cleveland Avenue, Suite 500 Fort Myers, FL 33907 COA 1

www.tlc-engineers.com P 239.275.4240 TLC No.:721030 THINK, LISTEN, CREATE,

DESIGN PROCUREMENT CONSTRUCTION



TLC | ENGINEERING | SOLUTIONS | SOLUTIONS | SOLUTIONS | SOLUTIONS | SCopyright 2019 | Suite 500 | Fort Myers, FL 33907 | COA 15 | P 239.275.4240 | Www.tlc-engineers.com | TLC No.:721030 |

COA 15
www.tlc-engineers.com
TLC No.:721030
THINK. LISTEN. CREATE.

ITEM	SYSTEM	COODE	DESIGN	PROCUREMENT	CONSTRUCTION
ITEM	STSIEM	SCOPE	RESPONSIBILITY	RESPONSIBILITY	RESPONSIBILITY
1.00	VOICE SYSTEM (TELEPHONE COMMUNICA	ATIONS SYSTEM ALL AREAS)			
1.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
1.02	INSIDE PREMISE WIRING	Structured cabling system, including patch cords	A&E	GC	GC
1.03	OUTSIDE PREMISE WIRING IN PRIVATE CAMPUS	Structured cabling system	A&E	GC	GC
1.04	OUTSIDE PREMISE WIRING FROM SERVICE PROVIDERS	Fiber and copper for services	A&E/OWNER	S.P.	S.P.
1.05	COUNTY FIBER BACKBONE TO DISTRICT FIBER LOOP	Fiber, conduit, pullboxes, etc.	OWNER/VENDOR	VENDOR	VENDOR
1.06	PATCHING OF VOICE LINES	labor only of patching at racks and work areas	A&E	N.A.	OWNER
1.07	PHONE SWITCH - ADMIN PHONES	Equipment selection, sizing, equipment layout, RFP	OWNER	GC	GC
2.00	DATA SYSTEM (COMPUTER NETV	VORKS ALL AREAS)			
2.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
2.02	INSIDE PREMISE WIRING	Structured cabling system, including patch cords	A&E	GC	GC
2.03	PATCHING OF DATA LINES	labor only of patching at racks and work areas	A&E	N.A.	OWNER
2.04	ACTIVE ELECTRONICS (NETWORKING EQUIPMENT, SWITCHES, ROUTERS, SERVERS AND COMPUTERS)	Equipment selection, sizing, equipment layout, RFP	OWNER	GC	OWNER
2.05	WIRELESS SURVEY	Modeling to predict location of WAPs, including measured survey after building shell is completed	A&E	N.A.	OWNER
2.06	WAPs	Wireless access points, including installation labor, support materials	OWNER	GC	GC
2.07	END POINT MEDIA CONVERTERS	Media converters, power supplies	OWNER	GC	GC
3.00	TELECOM ROOM O		O THILLI		
3.01	PLYWOOD AND WALL SLEEVES	Plywood and sleeves for cables	A&E	GC	GC
3.02	GROUNDING SYSTEM	Ground bar and ground bus	A&E	GC	GC
3.02	RACKS, WIRE MANAGERS AND LADDER TRAY	Racks and all passive elements	A&E	GC	GC
4.00	CATV DISTRIBUTION (CABLE TV	,	7101		
4.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
4.02	INSIDE PREMISE WIRING	Coaxial cable	A&E	GC	GC
4.03	DISTRIBUTION DEVICES	Taps, amplifiers, splitters, etc.	S.P	S.P	S.P
4.04	DISPLAYS	Displays/Monitors/TVs	A&E/OWNER	GC	GC
4.04	MOUNTS FOR TVS	Mounts for the TVS	A&E/OWNER	GC	GC
5.00	PAGING SYSTEM & DIGITA		A&E/OVVINER	GC	GC
5.00	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
	INSIDE PREMISE WIRING	Wiring for paging and digital signage systems	A&E	GC	GC
5.02					
5.03	ACTIVE ELECTRONICS	Paging system	A&E/OWNER	GC	GC
5.04	WAYSIDE SIGNAGE, CLEVER MONITORS	Wayside Signage, Clever monitors	A&E/OWNER	GC	GC
6.00	BUILDING CCTV AND ACCE		Λ0Γ	00	00
6.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
6.02	INSIDE PREMISE WIRING	Cables for cameras and card access	A&E	GC	GC
6.03	CCTV ACTIVE ELECTRONICS	Cameras and mounts	A&E/OWNER	GC	GC
6.04	CCTV SOFTWARE LICENSES	Software licenses for cameras	A&E/OWNER	GC	OWNER
6.05	CCTV VIDEO MANAGEMENT SYSTEM	DVRs	A&E/OWNER	GC	OWNER
6.06	ACCESS CONTROL ACTIVE ELECTRONICS	Access control panels, readers, etc	A&E	GC	GC
6.07	LOCKING DEVICES	Magnets, electric mortise locks	A&E	GC	GC
7.00	EMERGENCY POWER BACKUP (UPS)				
7.01	POWER WIRING	Conduit, cables and circuits	A&E	GC	GC
7.02	POWER DISTRIBUTION UNITS	ePDUs to be installed in rack	OWNER	GC	GC
7.03	ACTIVE EQUIPMENT - SMALL UNITS < 10KVA	UPS units in rack	OWNER	GC	GC
8.00	FIRE ALARM AND BUILDING MAN				
8.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
8.02	INSIDE PREMISE WIRING	Cabling, grounding	A&E	GC	GC
8.03	ACTIVE ELECTRONICS	Data gathering panels, sensors, etc	A&E	GC	GC
9.00 DISTRIBUTED ANTENNA SYSTEM (PUBLIC SAFETY)					
9.01	RACEWAYS	Conduit, boxes, cable tray, etc.	A&E	GC	GC
9.02	INSIDE PREMISE WIRING	Cabling, grounding	A&E	GC	GC
9.03	ACTIVE ELECTRONICS	Head end system, BDA, TX/RX and antennas	A&E	GC	GC

LeeTran Park & Ride Expansion

DESIGN AND CONSTRUCTION RESPONSIBILITIES

NOTES: A&E: ARCHITECT AND ALL CONSULTANTS WORKING UNDER ARCHITECT, LIKE TLC ENGINEERING SOLUTIONS

GC: GENERAL CONTRACTOR

S.P.: SERVICE PROVIDER

VENDOR: A SYSTEM INSTALLER HIRED DIRECTLY BY THE OWNER FOR A SPECIFIC SYSTEM

<u>KEYNOTES \bigcirc :</u>

1. PROVIDE POLYMER CONCRETE COMMUNICATIONS VAULT. THE DIMENSIONS SHALL BE A MINIMUM OF 3'-0" L X 2'-0" D. ENGRAVE ON TOP LID "COMMUNICATIONS" IN 2" LETTERS. REFER TO DETAIL FOR MORE INFORMATION.

2. PROVIDE 20" L X 12" W X 20" D POLYMER CONCRETE VAULT. ENGRAVE "COMMUNICATIONS" IN 2" LETTERS ON LID. REFER TO SPECIFICATION 270528 FOR MORE INFORMATION ON POLYMER CONCRETE REQUIREMENTS.

3. PROVIDE THREE (2) 2" CONDUITS AND ONE (1) 4" CONDUIT TO I.T. ROOM. REFER TO FLOOR PLAN FOR STUB UP LOCATION.

4. PROVIDE TWO (2) 2" CONDUITS.

5. PROVIDE ONE (1) 2" CONDUIT.


6. A 16" X 16" NEMA 4X ENCLOSURE WITH KEY LOCKABLE DOOR AT 4'-0" AFF. PROVIDE A LAYER OF 1" POLYISO IN ALL INTERIOR SURFACES. PROTECT INSULATION WITH ALUMINUM TAPE.

HORIZONTAL DISTRIBUTION NOTES:

1. TERMINATE STRUCTURED TELECOMMUNICATIONS DATA CABLING IN THIS AREA ON PATCH PANEL INSTALLED IN RACKS IN I.T. ROOM, UNLESS OTHERWISE NOTED.

2. TERMINATE SECURITY SYSTEM CABLING IN THIS AREA AT SECURITY EQUIPMENT INSTALLED IN I.T. ROOM, UNLESS

3. TERMINATE PUBLIC ADDRESS SYSTEM CABLING IN I.T. ROOM, UNLESS OTHERWISE NOTED.



TLC | ENGINEERING | SOLUTIONS uite 500
ort Myers, FL 33907
239.275.4240
THINK. LISTEN. CREATE.

GENERAL NOTES:

PROVIDE SURGE SUPRESSION DEVICES IN THE IT ROOM FOR ALL HORITZONTAL 4-PAIR UTP CABLES ROUTED OUTSIDE OF BUILDING OR TO DEVICES ON THE EXTERIOR OF THE BUILDING.

<u>KEYNOTES</u>

1. DATA DEDICATED FOR CLEVER SIGN. PROVIDE 6"X 6" ELECTRICAL BOX WITH SINGLE GANG DEVICE ADAPTER AND A SURFACE MOUNT OUTLET (BISCUIT JACK) WITH SINGLE CATEGORY JACK MOUNTED INSIDE.

2. PROVIDE 6"X6" ELECTRICAL BOX.


3. PROVIDE 1.5" UNDERGROUND CONDUIT TO IT ROOM 7.

1. TERMINATE STRUCTURED TELECOMMUNICATIONS DATA CABLING IN THIS AREA ON PATCH PANEL INSTALLED IN RACKS IN I.T. ROOM, UNLESS OTHERWISE NOTED.

2. TERMINATE SECURITY SYSTEM CABLING IN THIS AREA AT SECURITY EQUIPMENT INSTALLED IN I.T. ROOM, UNLESS

3. TERMINATE PUBLIC ADDRESS SYSTEM CABLING IN I.T. ROOM, UNLESS OTHERWISE NOTED.

ENLARGED PLAN - SIDE 2 CANOPY - TECHNOLOGY
1/8" = 1'-0"



1 FLOOR PLAN - TECHNOLOGY
1/4" = 1'-0"

GENERAL NOTES:

1. PROVIDE SURGE SUPRESSION DEVICES IN THE IT ROOM FOR ALL HORITZONTAL 4-PAIR UTP CABLES ROUTED OUTSIDE OF BUILDING OR TO DEVICES ON THE EXTERIOR OF THE BUILDING.

KEYNOTES :

- 1. LOCATE CONDUIT STUBS FROM COMMUNICATION VAULT TYPE 1 HERE AND AS CLOSE TO WALL AS POSSIBLE TO ELIMINATE INTERFERING WITH EQUIPMENT CLEARANCES.
- 2. PROVIDE 2 POST RACK WITH 6" VERTICAL WIRE MANAGERS ON EACH SIDE.
- 3. PROVIDE GROUND BUSBAR.
- 4. PROVIDE 8' H X 4' W X 3/4" D PLYWOOD. INSTALL AT 4" AFF TO 8'-4" AFF.
- 5. SPACE DEDICATED FOR WALL MOUNTED ACCESS CONTROL EQUIPMENT.
- 6. SPACE DEDICATED FOR DEMARC / SERVICE PROVIDER EQUIPMENT.
- 7. DATA DEDICATED FOR VENDING MACHINE.
- 8. DATA DEDICATED FOR TICKENT VENDING MACHINE.
- 9. DATA DEDICATED FOR CLEVER MONITOR.
- 10. LOCATE CONDUIT STUBS FROM COMMUNICATION VAULT TYPE 2 HERE AND AS CLOSE TO WALL AS POSSIBLE TO ELIMINATE INTERFERING WITH EQUIPMENT CLEARANCES.
- 11. LOCATE 1-1/2" CONDUIT STUBS FROM CANOPY DEVICES HERE AND AS CLOSE TO WALL AS POSSIBLE TO ELIMINATE INTERFERING WITH EQUIPMENT CLEARANCES.
- HORIZONTAL DISTRIBUTION NOTES
- TERMINATE STRUCTURED TELECOMMUNICATIONS DATA CABLING IN THIS AREA ON PATCH PANEL INSTALLED IN RACKS IN I.T. ROOM, UNLESS OTHERWISE NOTED.
- 2. TERMINATE SECURITY SYSTEM CABLING IN THIS AREA AT SECURITY EQUIPMENT INSTALLED IN I.T. ROOM, UNLESS OTHERWISE NOTED.
- 3. TERMINATE PUBLIC ADDRESS SYSTEM CABLING IN I.T. ROOM, UNLESS OTHERWISE NOTED.

JDGETT / SMITH ARCH


REVISIONS


No. Description Date












TELECOMMUNICATIONS VAULT - POLYMER CONCRETE WITH

4 OPEN BOTTOM 1" = 1'-0"

—CONDUIT OR J-HOOK SUPPORTS AS REQUIRED (TYPICAL) PROVIDE CONDUIT WHEN THE CEILING IS INACCESSIBLE AND J-HOOKS ABOVE ACCESSIBLE CEILING TILES UNLESS NOTED OTHERWISE IN PROJECT SPECIFICATIONS. REFER TO SPECIFICATIONS 270528 REGARDING THE USE OF J-HOOKS IN THIS SPECIFIC PROJECT. PROVIDE 1" CONCEALED CONDUIT PROVIDE TELECOMMUNICATIONS OUTLET BOX WITH SINGLE GANG MUD RING. REFER TO SPECIFICATION 270528 FOR FLOOR SYMBOL USED FN FLOOR PLAN N: DENOTES # OF CABLES


COMMUNICATIONS BACKBOX

0UTLET AND CONDUIT
1/2" = 1'-0"



OUTLET FOR MECH/ELEC/ELEV

2 CONNECTION - TYPE 1



3 FLUSH MOUNTED OUTLET





REVISIONS

No. Description Date

RIDE AND **ACRES PARK** EHIGH.